

CAP-100LIV

- 1, 4, 6, 9, 10, 16, 32 multi channel view support
- Normal 1, 4, 9, 16 multi channel switching TV-out support
- Motion detection and sensor activation
- 1~16 channel sound recording
- Normal / Multi / Icon / Panorama / Smart search
- Pan / Tilt / Zoom / Focus control support
- Hardware Watchdog for auto rebooting
- Save to a file as watermark image
- E-mail event alert
- Voice message notification to a telephone
- IP address dispatch (for use with dynamic IP)
- Various event notifications — Beep, Mark, Popup, TV-out popup, Second screen popup, DiViS-net notify, Relay output, E-mail, PTZ Preset, Phone call



Specifications

Model Number	CAP-100LIV
Camera Input	16 Channel
Sensor Input	16 Channel
Relay Output	4 Channel
Composite Output	1 Channel (Multi channel switching - Normal 1, 4 view) 2 Channel (Optional 4, 16 channel)
Audio Input	Software MPEG-4 CODEC
Compression CODEC	352 x 288, 704 x 288, 704 x 576
Resolution	400fps
Maximum Display	100fps
Maximum Recording	RS 232 / 422 / 485 port
PTZ Interface	TCP/IP, RS 232 / 422 / 485, Parallel (Optional)
POS/AC/ATM Interface	DiViS, DiViS-Net, DiViS-Web, PDA, CMS
Software	

Screen Shots

